



Motor/Horsepower/Voltage Selection and Starter Requirement Chart

Motor	Option No.	Voltage		208/1/60	230/1/60	208/3/60	230/3/60	460/3/60	575/3/60
		HP	RPM	AK2	AK3	AK5	AK6	AK7	AK8
Open Dripproof Motor for Belt Drive	AL3	1/3	1,725	X ^A	X ^A	X ^{A D}	X ^{A D}	X ^{A D}	N/A
	AL4	1/2	1,725	X	X	X	X	X	N/A
	AL5	3/4	1,725	X	X	X	X	X	N/A
	AL6	1	1,725	X	X	X	X	X	X ^D
	AL7	2	1,725	X	X	X	X	X	X ^D
	AL8	2	1,725	X ^D	X ^D	X	X	X	X ^D
	AL9	3	3,600	X ^{B D}	X ^{B D}	X ^B	X ^B	X ^B	X ^{B D}
AL10	5	3,600	X ^{C D}	X ^{C D}	X ^{C D}	X ^{C D}	X ^{C D}	X ^{C D}	
Totally Enclosed Motor for Belt Drive	AL20	1/3	1,725	X	X	X ^D	X ^D	X ^D	N/A
	AL21	1/2	1,725	X	X	X	X	X	X ^D
	AL22	3/4	1,725	X	X	X	X	X	X ^D
	AL23	1	1,725	N/A	X	X	X	X	X ^D
	AL24	2	1,725	X	X	X	X	X	X ^D
	AL25	2	1,725	N/A	X ^D	X ^D	X ^D	X ^D	X ^D
	AL26	3	3,600	N/A	X ^{B D}	X ^{B D}	X ^{B D}	X ^{B D}	X ^{B D}
AL27	5	3,600	N/A	X ^{B D}	X ^{B D}	X ^{B D}	X ^{B D}	X ^{B D}	
Premium Efficiency Motor for Belt Drive	AL36	1	1,800	N/A	N/A	X ^D	X ^D	X ^D	X ^D
	AL37	1 1/2	1,800	N/A	N/A	X ^D	X ^D	X ^D	X ^D
	AL38	2	1,800	N/A	N/A	X ^D	X ^D	X ^D	X ^D
	AL39	3	1,800	N/A	N/A	X ^{B D}	X ^{B D}	X ^{B D}	X ^{B D}
	AL40	5	1,800	N/A	N/A	X ^{C D}	X ^{C D}	X ^{C D}	X ^{C D}

^A Sizes 150-300 only.

^B Sizes 250-400 only.

^C Sizes 300-400 only.

^D Require Motor Starter (Reznor Option AN10)